

DESCRIPTION & FEATURES

6000 counts true RMS digital multimeter

Non-contact voltage detection
live line or neutral Line distinguish
DC Voltage:

600mV/6V/60V/600V/1000V $\pm(0.5\%+3)$

AC Voltage: 6V/60V $\pm(0.8\%+3)$

600V/750V $\pm(1.0\%+10)$

DC Current: 60 μ A/60mA/600mA

$\pm(0.8\%+3)$ 10A $\pm(1.2\%+3)$

AC Current: 60mA/600mA $\pm(1.0\%+3)$


10A $\pm(1.5\%+3)$

Resistance: 600 Ω /6k Ω /60k Ω /600k

Ω /6M Ω $\pm(0.8\%+3)$

60M Ω $\pm(1.0\%+30)$

CAT III 1000V
CAT IV 600V



SELLING POINTS

Fully functional

IDM7502

DIGITAL MULTIMETER

FUNCTION

Used for circuit testing, fault diagnosis, current measurement, voltage detection